

# FaleMais

VOIP



A configuração deste Telefone IP consiste em acessar o seu software de configuração através do seu navegador web (**browser**). Caso você não saiba o endereço IP do seu Telefone IP GXP280, é possível obtê-lo pelo visor do aparelho, teclando **MENU** em seguida com as setas direcionais selecione **Status** e clique em **Menu** novamente. O aparelho irá lhe mostrar no LCD o endereço de IP em que ele se encontra.



1. No caso do nosso exemplo, o nosso Telefone IP se encontra no IP 10.11.2.22 e para acessá-lo basta digitarmos o IP na barra de endereços do seu navegador de internet ex. (Google chrome). Certifique-se que este IP está liberado de qualquer proxy configurado no navegador;

2. Clique em Account:

**Grandstream Device Configuration**

STATUS	BASIC SETTINGS	ADVANCED SETTINGS	ACCOUNT
--------	----------------	-------------------	---------

  

**Account Name:**  (e.g., MyCompany)

**SIP Server:**  (e.g., sip.mycompany.com, or IP address)

**Outbound Proxy:**  (e.g., proxy.myprovider.com, or IP address)

**SIP User ID:**  (the user part of an SIP address)

**Authenticate ID:**  (can be same or different from SIP UserID)

**Authenticate Password:**  (not displayed for security protection)

**Name:**  (optional, e.g., John Doe)

**Use DNS SRV:**  No  Yes

**User ID is phone number:**  No  Yes

**SIP Registration:**  No  Yes

**Unregister On Reboot:**  No  Yes

**Register Expiration:**  (in minutes. default 1 hour, max 45 days)

**local SIP port:**  (default 5060)

**SIP Registration Failure Retry Wait Time:**  (in seconds. Between 1-3600, default is 20)

**SIP T1 Timeout:**

**SIP T2 Interval:**

**SIP Transport:**  UDP  TCP

**Use RFC3581 Symmetric Routing:**  No  Yes

**NAT Traversal (STUN):**  No  No, but send keep-alive  Yes

**SUBSCRIBE for MWI:**  No  Yes

**Proxy-Require:**

**Voice Mail UserID:**  (UserID for voice mail system)

**Send DTMF:**  in-audio  via RTP (RFC2833)  via SIP INFO

**Early Dial:**  No  Yes (use "Yes" only if proxy supports 484 response)

No campo **Account Name** preencha: seu nome;

Nos campos **SIP Server** e **Outbound Proxy** preencha: sip.falemaisvoip.com.br;

Nos campos **SIP User ID** e **Authenticate ID** preencha: Usuário (FaleMais)

No campo **Password** para Autenticação preencha: Sua senha (FaleMais)

O campo **Use DNS Server** deverá ser informado Sim;

O campo **User ID is phone Number** deverá ser informado Não;

O campo **SIP Registration** deverá ser informado Sim;

O campo **Unregister On Reboot** deverá ser informado Não;

O campo **Register Expiration** deverá ser informado 6;

O campo **Send DTMF** deverá ficar marcado somente via RTP(RFC2833);

Role a pagina até o fim e clique em **Update** e em seguida **Reboot**;